

XIOS PLC Application



- Extensive PLC functions
- ✓ Flexible by programming on the basis of CoDeSys*
- ✓ MATLAB™/Simulink* interface for easy coding
- ✓ Scalable number of I/O boards, modular design
- ✓ I/Os individually configurable by software

The HEINZMANN modular universal controller XIOS UC 1 presents an entirely new generation of controller. In particular it offers extensive PLC functions.

The basic high performance main board (MC) of XIOS UC 1 comes equipped with 13 inputs and 2 outputs. 9 further I/O modules (MA) can be attached to it, each able to serve several further I/O channels. Additionally, one more expander module (MD 1) offering 8 more configurable I/O channels as well as 2 outputs and 4 inputs can be attached. At last each expander module provides connection of 6 further I/O modules (MA) as well.

The jumperless I/O boards are configurable by software. They can be attached in different number and type to the main board.

XIOS UC 1 enables customers to develop their own functions on the basis of CoDeSys* (IEC 61131-3) or MATLAB™/ Simulink*. This allows building up extensive and flexible functions.

Ethernet, CAN, RS-232 and RS-485 are supplied as communication interfaces, USB for peripherals. Connections to XIOS are simply established via screwless quick-set terminals.

Module type	I/Os	Module Extensions
Main board (MC)	13× input	5× slot for module type MA
, ,	2× output	1× slot for module type MD 1

Expander board (MD 1)	12× input	6× slot for module type MA
	2× output	

Extension boards (MA)	Each configurable by software
A1	2× thermocouple amplifier
A2	4× analogue or digital outputs
A3	4× analogue or digital inputs
A4	2× analogue or digital inputs, electrically isolated
A5	2× analogue or digital outputs, electrically isolated
A6	2× analogue outputs, electrically isolated
A7	6× digital inputs
A8	2× digital outputs half bridge
A9	1× full bridge output (4Q)

^{*} All trademarks are the property of their respective owners.

Subject to changes and corrections. ©Heinzmann GmbH & Co. KG, 2017

